

Page 1 of 3	<b>Wall Mount P3Link Patch Panel Houses up to 8 MAP Adapter Plates</b>	Date: 10/31/13
<b>WMP08P</b>		Rev 0



*Opticonx  
WMP08P*

## 1.0 General

This data sheet covers the mechanical and performance characteristics of Opticonx WMP12P wall mount patch panel.

## 2.0 Application

This wall mount patch panel enclosure is used in conjunction with Opticonx MAP series adapter plates and P3Link Xtreme cassettes. It houses up to 8 MAP adapter plates. It is wall mountable with a footprint of 12" High x 15" Wide.

## 3.0 Mechanical Specifications

### 3.1 Dimensions

12.0" High x 15.0" Wide x 6.0" Deep

### 3.2 Weight

17.5 Lbs.



Opticonx, Inc.  
45 Danco Road  
Putnam, CT 06260  
Toll Free: 888 748-6855  
www.opticonx.com



Page 2 of 3	<b>Wall Mount P3Link Patch Panel Houses up to 8 MAP Adapter Plates</b>	Date: 10/31/13
<b>WMP08P</b>		Rev 0

#### **4.0 Construction**

##### **4.1 Material**

16 Gauge cold rolled steel body, and doors.

##### **4.2 Finish**

Epoxy powder coat, Black textured finish.

##### **4.3 Field Assembly Requirements**

The enclosure is shipped completely assembled for wall mounting.

#### **5.0 Features**

##### **5.1 Mounting**

The enclosure can be mounted on 3/4" plywood backer board through four (4) embossed mounting holes. When mounted the unit is 16.0" High x 14.0" Wide by 7.0" Deep.

##### **5.2 Cable Management**

Fiber optic cable management clips are installed in both the left and right side compartments. The cable management clips and compartment size are designed to route incoming cables to the fiber adapters and cassettes and the jumpers out of the top or bottom of the box.

##### **5.3 Cable Entry/Exit**

Two cable entry holes are located on the top and bottom of the enclosure. The top and bottom holes accept standard 1.75" connectors. One "U" shaped entry/exit slot is located on the user/patch side top and bottom. Dust caps are included for unused entry/exit holes.

##### **5.4 Doors**

The panel features double doors that isolate the technician compartment from the patch/user compartment. Both doors are lockable.



Opticonx, Inc.  
45 Danco Road  
Putnam, CT 06260  
Toll Free: 888 748-6855  
www.opticonx.com



Page 3 of 3	<b>Wall Mount P3Link Patch Panel Houses up to 8 MAP Adapter Plates</b>	Date: 10/31/13
<b>WMP08P</b>		Rev 0

### 5.3 Connector Panel

The connector panel accepts up to 8 MAP adapter plates or 8 P3Link Cassettes (up to 16 P3Link Xtreme cassettes when used with retrofit bracket kit P3XRF-2). Total maximum port density for LC connectors is 192 fibers.

### 5.4 Included Parts and Accessories

- (2) 1.75" Dust Caps
- (2) 6" Cable Ties
- (2) 1.75" Through Hole Grommets
- (1) Port ID Label
- (1) Laser Warning Label



Opticonx, Inc.  
45 Danco Road  
Putnam, CT 06260  
Toll Free: 888 748-6855  
[www.opticonx.com](http://www.opticonx.com)

