

Page 1 of 3	Wall Mount P3Link Patch Panel Houses up to 4 MAP Adapter Plates	Date: 10/31/13
WMP04P		Rev 0



*Opticonx
WMP04P*

1.0 General

This data sheet covers the mechanical and performance characteristics of Opticonx WMP04P wall mount patch panel.

2.0 Application

This wall mount patch panel enclosure is used in conjunction with Opticonx MAP series adapter plates and P3Link Xtreme cassettes when used with retrofit bracket kit P3XRF-2. It houses up to 4 MAP adapter plates. It is wall mountable with a footprint of 12" High x 15" Wide.

3.0 Mechanical Specifications

3.1 Dimensions

12.0" High x 15.0" Wide x 3.5" Deep

3.2 Weight

16.0 Lbs.



Opticonx, Inc.
45 Danco Road
Putnam, CT 06260
Toll Free: 888 748-6855
www.opticonx.com



Page 2 of 3	Wall Mount P3Link Patch Panel Houses up to 4 MAP Adapter Plates	Date: 10/31/13
WMP04P		Rev 0

4.0 Construction

4.1 Material

16 Gauge cold rolled steel body, and doors.

4.2 Finish

Epoxy powder coat, Black textured finish.

4.3 Field Assembly Requirements

The enclosure is shipped completely assembled for wall mounting.

5.0 Features

5.1 Mounting

The enclosure can be mounted on 3/4" plywood backer board through four (4) embossed mounting holes. When mounted the unit is 12.0" High x 15.0" Wide by 3.5" Deep.

5.2 Cable Management

Fiber optic cable management clips are installed in both the left and right side compartments. The cable management clips and compartment size are designed to route incoming cables to the fiber adapters and cassettes and the jumpers out of the top or bottom of the box.

5.3 Cable Entry/Exit

Two cable entry slots are located on the top and bottom of the enclosure in each patching compartments. Dust caps are included for unused entry/exit holes.

5.4 Doors

The panel features double doors that isolate the technician compartment from the patch/user compartment. Both doors are lockable.



Opticonx, Inc.
45 Danco Road
Putnam, CT 06260
Toll Free: 888 748-6855
www.opticonx.com



Page 3 of 3	Wall Mount P3Link Patch Panel Houses up to 4 MAP Adapter Plates	Date: 10/31/13
WMP04P		Rev 0

5.3 Connector Panel

The connector panel accepts up to 4 MAP adapter plates or 4 P3Link Cassettes (up to 8 P3Link Xtreme cassettes when used with retrofit bracket kit P3XRF-2). Total maximum port density for LC connectors is 96 fibers.

5.4 Included Parts and Accessories

- (2) 6" Cable Ties
- (4) "U" Shaped Dust Caps
- (1) Port ID Label
- (1) Laser Warning Label



Opticonx, Inc.
45 Danco Road
Putnam, CT 06260
Toll Free: 888 748-6855
www.opticonx.com

